Reolink

Reolink Lumus

Spotlight 2560p WiFi Security Camera; Brighten up Your Surroundings and Deter Criminals

- · 2560p Full HD
- · Motion Spotlight
- · Two-Way Audio

Specifications

Video & Audio	
Image Sensor	1/2.7" CMOS Sensor
Resolution	2560 x 1440 (4.0 Megapixels) @15fps
Lens	f=2.8mm, F=2, with IR Cut
Video Compression	H.264
Field of View	Horizontal: 107° Vertical: 57° Diagonal: 129°
Infrared Night Vision	Up to 10m (33ft) (LED: 6pcs/0.8W/ 850nm) (Auto-switching with IR-cut filter)
Color Night Vision	With spotlights: 2pcs/1.6W/6500K
Frame Rate	Main stream: 2fps - 15fps (default: 15fps) Sub stream: 4fps - 15fps (default: 10fps)
Code Rate	Main stream: 1024Kbps - 3072Kbps (default: 3072Kbps) Sub stream: 64Kbps - 512Kbps (default: 256Kbps)
Audio	Two-way audio

Power Requirements		
Power Requirements	DC 5.0V圖1A, <5W	
Interface		
Power Port	DC power port	
SD Card Slot	Supports Max. 256GB microSD card	
Reset Button	YES	
Audio In/Out	Built-in microphone and speaker	
Wi-Fi		
Wireless Standard	IEEE 802.11 a/b/g/n	
Operating Frequency	2.4GHz/5GHz	
Wireless Security	WPA/WPA2	
Software		
Browsers Supported	No	
OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android	
Protocols & Standards	SSL, TCP/IP, UDP, UPNP, SMTP, NTP, DHCP, DNS, DDNS, P2P	
User Access	Max.20 users (1 admin & 19 users); Max. 12 simultaneous streams (2 main & 10 sub streams)	
Other Feature(s)		
Smart Alarm	Motion detection; person detection; vehicle detection; animal detection	
Recording Modes	Motion-triggered recording (default); Scheduled recording; 24/7 recording	
Time Lapse	YES	
Smart Home Compatibility	Google Assistant; Alexa	
Working Environment		
Temperature	Operating Temperature: -10°C ~ 55°C	
Humidity	Operating Humidity: 20% ~ 85%	

Waterproof	IP65	
Mechanical		
Dimensions	99 x 91 x 60mm	
Weight	168g	
Warranty		
Limited Warranty	2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/	

Gallery & Specs



- 1. Status LED
- 2. Spotlight
- 3. Lens
- 4. Daylight Sensor
- 5. IR LEDs
- 6. Built-in Mic



- 1. Speaker
- 2. Bracket
- 3. Reset Button
- 4. microSD Card Slot

www.reolink.com